
MATHEW TECH KC108

3-Mode RGB Mechanical Keyboard

<http://www.mathewkb.com>

Version:1.0

2024/07/27

By:MATHEW

1. 108keys layout



2. FN Combination

	Combination	function	description
FN +	ESC	Reset (3S)	
	F1	Computer	
	F2	Home	
	F3	Email	
	F4	Search	
	F5	Music	
	F6	Play / Pause	
	F7	Previous song	
	F8	Next song	
	←	Speed down	
	→	Speed Up	
	↑	Brightne Up	
	↓	Brightne down	
	Q	Bluetooth 1	
	W	Bluetooth 2	
	E	Bluetooth 3	
	R	2.4G	
	Tab (3S)	Wired/Wireless)	
	Backspace	Battery Percentage	
	A	Win Mode	
	S	Mac Mode	
	Win	Lock Win	
	Prtsc	Switch on/off RGB	
	Insert	RGB mode switch	
	Shift(right)	Factory Reset	

3. Bluetooth/2.4G/Wired Pairing/Software:

2.4G Pairing:After the keyboard is turned on,Press Fn+R to enter 2.4G mode.at this time,the R flash slowly,Long press Fn+R for 3seconds to enter Pairing mode.the R flash quickly,plug the receiver now.after pairing success,The R will stop flashing.

(Since 2.4G communication is easily affected by wifi and bluetooth frequency,if connection failed for the first time,try temporarily turn off the wifi and bluetooth at home, reset the keyboard(Fn+esc for 3seconds),then continue to connect.once the connection succeed,it will basically not failed again.)

Bluetooth pairing:After the keyboard is turned on,Press Fn+Q/W/E to enter bluetooth mode.at this time,the Q/W/E flash slowly,Long press Fn+Q/W/E for 3seconds to enter Pairing mode.the Q/W/E flash quickly,open your computer bluetooth and searching,once keyboard show up,connect the keyboard.after pairing success,The Q/W/E will stop flashing.

Wired connection:turn off the keyboard and plug type-c cable,if in wireless mode, Press Fn+Tab for 3second change to wired mode.

Software connection:turn off the keyboard and plug type-c cable.