

# MK96 User Manual

## Standard specs:

USB - Type C; Gasket mount

Cable length: 1.5m

Battery: 6000mAh

Weight: 940g+-20g

Supported systems: MAC/ Win/ Linux/  
IOS/Android

## Function key combination

FN + F1: Brightness decrease

FN + F2: Brightness increase

FN +F3: Win +Tab / Mission control

FN + F4: Win + E / Siri

FN + F5: Email / None

FN + F6: Homepage / None

FN + F7: Previous song

FN + F8: Play/Pause

FN + F9: Next song

FN + F10: Mute

FN + F11: Volume down

FN + F12: Volume up

FN + 1: Bluetooth 1

FN + 2: Bluetooth 2

FN + 3: Bluetooth 3

FN + 4: 2.4G

FN + 5: Wired (hold for 5s)

FN + Win: Win lock

FN + Backspace: Backlight On/Off

FN + up arrow = Backlight up

FN + down arrow: Backlight down

FN + left arrow; Backlight speed -

FN + right arrow: Backlight speed +

FN + Esc: Reset

FN + W: Win

FN + M: Mac

Knob: Volumn adjust/Press to mute

## Wireless Connection

**2.4G connection:** Press FN+4 to switch 2.4G mode, white light the right side will flash slowly. Continue to press and hold for 3s to connect, plug receiver in when the light flashes rapidly. Light stops flashing when connected successful. If the device is not successfully paired after 30 seconds, the light signal will be off, the key returns to the standby state.

**Ble connection:** Press FN + 1/2/3 to turn on Bluetooth mode, continue press and hold for 3s to connect. The signal light now flashes quickly, connect success when the light is off.

**How to fix 2.4G connection error:** 2.4G connection is susceptible to interference by wifi and bluetooth, if the first pairing fails, try temporarily turning off wifi and bluetooth transmitters in the house, reset keyboard, then try connecting again. Alternatively, plug in another USB port or place the keyboard next to the device to be connected. Normally when connected success won't get the error anymore.

## Friendly reminder:

**When using keymap software:** Switch wired mode and plug the cable in before use. Turn off firewall/ anti-virus software if the software does not receive the key, or reset the keyboard, run the uploaded firmware on the website.

**Check battery:** FN + B (number 1-0 backlight lights up shows the remaining battery percentage.)

## Website:



## Facebook:



**mathewkb.com**